

WIZARD ECO 100

Speed/Area Meter

FEATURES/BENEFITS

- Powered from 2 x AA batteries instead of the normally required connection to a vehicle battery - provides ease of installation and transfer between applications.
- Large display and buttons - ease of use for the operator.
- Wizard 'ECO 100' automatically goes into 'standby' mode after 10 minutes of non use and 'woken' by 1st sensor pulse - this prolongs battery life.
- 'Lo Batt' indication - advises of battery replacement to avoid operator using machine without Wizard 'ECO 100' information.
- All information stored even if the battery is removed - re-calibration is then not necessary.
- Easily programmable speed and width factor - provides accurate speed and area accumulation on any machine.
- Sealed to IP67 - ensuring reliable operation in harsh environments.
- Supplied with a mounting bracket and a single high quality reed sensor & magnet - provides easy installation and system reliability.
- Visually identical to the popular RDS Wizard - a more sophisticated instrument in the RDS product family, 1000's of which are now in use on many different applications including seed drills.
- Economic Speed/Area meter solution for simple machine applications.



CUSTOMIZABLE OPTIONS:

- Extra sensor input for either area cut-out or shaft speed by software.
- Upto 4 separate area registers available by software modification.

